

Setting a Constant Recording Schedule



To set the DVR to constantly record you will need to go to the **Configure** Icon in the main menu, this is shown below:



Then click the **Record Setup**, icon is circled below:





This will open the following menu; in here you will need to **un-tick the Continuous Record** tick boxes for all the channels which you would like to be on continuous recording. Then you will need to make sure that all **corresponding Event Record boxes are un-ticked**. Your settings should look similar to the below:

Record Setup										
Record Mode:										
	Continuou	s Record	Schedule R	ecord						
\triangleleft	CH01	CH02	CHOS	СН04 >						
Continuous Record										
Record										
Resolution	192001030	123011720	192011030	192011030						
FPS	12 🛛	12 0	12 D	12						
Quality	0 5 0	350	350	 5 0 						
Audio										
		Event Re	cord							
Record										
Resolution	1920X1030	123011720	192011080	1920X1030						
FPS	12 🛛	12 D	12 0	12)						
Quality	0 5 0	0 5 D	0 5 D	 5 0 						
Pre-Alarm	3)	3)	3)							
Post-Alarm		0 5)								
Audio										
	01		Cancel							

Once you have matched the settings you will need to click the **OK** button. Then **right click**, this will take you back to the previous menu. Once in the previous menu, click the **Event Setup** lcon shown below:





This will open a new menu; here you will need to click the **motion detection tab** along the top of the menu page. Now you will need to **un-tick the Enable box** for all the cameras you are setting for constant record. The setting should be similar to the below example:

2016/11/	1 (12/04/2)		251.9GB/ Event S	931.5GB Setup	2016/00 78200 01 -	Nov-16 PM 12:	04:43
		ideo Loss CH01	Motion D CH02	CH08	System CH04		
6	Enable						EI-S
2016/(1	Notification		Distance H				
						\square	
	Event Record	CH01	CHO2	CHOS) (CH04) (Disable 🖂	
a	Popup	Disable	Disable	Disable 🗸	Disable 🗸	Disable 🖂	
7	Popup Channel	CHO1	CH02	Chos 🗸) (CH04	Relative 🖂	
2015/11	Buzzer						
2010/11	() () () () () () () () () () () () () (
	Burgert						
	Resume Preset						
	Mail to	Recei	vər Sətup) (Notifi	cation Setup		1
				Cana			
	СН07		СН	08			

Once you have done this simply click the **OK** button to save the changes. Once this is done your Phoenix will now be constantly recording on channels you have just changed.